

FILM-TECH

THE INFORMATION CONTAINED IN THIS ADOBE ACROBAT PDF FILE IS PROVIDED AT YOUR OWN RISK AND GOOD JUDGMENT.

THESE MANUALS ARE DESIGNED TO FACILITATE THE EXCHANGE OF INFORMATION RELATED TO CINEMA PROJECTION AND FILM HANDLING, WITH NO WARRANTIES NOR OBLIGATIONS FROM THE AUTHORS, FOR QUALIFIED FIELD SERVICE ENGINEERS.

IF YOU ARE NOT A QUALIFIED TECHNICIAN, PLEASE MAKE NO ADJUSTMENTS TO ANYTHING YOU MAY READ ABOUT IN THESE ADOBE MANUAL DOWNLOADS.

WWW.FILM-TECH.COM

JB-9000 Surround Speaker Termination Panel

GENERAL

The KELMAR JB-9000 Speaker Terminal Box has been designed to provide a termination point for Auditorium Surround Speaker wires and for Screen Speaker conduits. The JB-9000 allows the Electrical Contractor to complete the installation of the Speaker conduits and pull in all wires prior to delivery and installation of the Sound Rack. The JB-9000 provides a convenient Termination and Test Point for Surround Speakers to minimize the wiring inside the Audio Rack.

JB-9000 Dimensions: 7" wide X 12" high X 3" deep.

The JB-9000 is intended to serve up to 12 Surround Speakers. For Auditoriums with more than 12 Surround Speakers and Bi or Tri- Amplification, use 2 or more JB-9000 Speaker Termination Boxes and more than 1 Screen Conduit.

The JB-9000 provides a Terminal Strip for a series / parallel Surround Speaker Connection. For Surround Arrays with less than even Speaker quantities, Resistors are provided to maintain proper Amplifier loading.

INSTALLATION

The JB-9000 should be located on the wall of the Projection Room at the Audio Rack. A typical installation is to locate the Audio Rack on the Operating Side of the Projector and the Platter on the Non-Operating side. For this installation, locate the Left Side of the JB-9000 8'-0" from the CENTERLINE of the Projection Port with the Bottom of the JB-9000 located at 4'-0" AFF.

Connection of the JB-9000 to the Audio Rack Should be made with Flexible Liquidtite or Sealtite Conduit. The JB-9000 has an opening on the bottom for a 1-1/4" Conduit to the Audio Rack. The top of the JB-9000 contains One opening for a 1-1/4" Screen Speaker Conduit and Two openings for 3/4" Surround Speaker Conduits. These can be punched to a larger size by the Electrical Contractor if required.

The 1-1/4" Sealtite to the Audio Rack Contains the Screen Speaker Wires plus 4 Wires for Left and Right Surround Speaker Arrays.

Refer to the following Termination Drawings:

NO.1453 for 6 or 8 Speakers

NO.1538 for 10 or 12 Speakers

If further information is required please contact:

Kelmar Systems Inc.

284 Broadway

Huntington Station, NY 11746

Phone (516) 421-1230 FAX (516) 421-1274



