Film-Tech

The information contained in this Adobe Acrobat pdf file is provided at your own risk and good judgment.

These manual s are designed to facil itate the exchange of information rel ated to cinema projection and film handling, with no warranties nor obligations from the authors, for qualified field service engineers.

If you are not a qual ified technician, pl ease make no adjustments to anything you may read about in these Adobe manual downloads.

www.film-tech.com

eulap

Film Splicer

1. Lift top jaw assembly to upright position - place roll of Neutape in splicer.

2. Using sprocket pins at right hand end of splicer bed, position film for straight splice so that frame line is centered over lower cutting blade (on diagonal model, place film accordingly). Trim right and then left hand film and position in splicer bed on center pins only, using red mark to locate ends of film butted together.

If dirt or oil is on the film in splice area, wipe with clean cloth to insure maximum tape adhesion.

3. Pull tape from supply roll across film lining up the tape with edge marks on front guide bracket. Press tape onto film to eliminate any air bubbles.

4. Lower top jaw assembly and press hand lever to full downward position. (This will trim tape at both edges of the film and perforate sprocket holes in tape). Lift top jaw assembly and again press tape to film across entire splice area.

5. Remove film from splicer, flip over to repeat Steps 3 and 4. This will produce a smooth, stable splice with tape on both sides of the film.

<u>NOTE:</u> On Model 16-SW (Wrap Around), after Step 2, position trimmed film emulsion up and apply tape as in Step 3. Trim and punch as in Step 4. Lift film from splicer, fold over perforated tab extension, wrapping tape around other side of film.

MAINTENANCE SUGGESTIONS

1. To take full advantage of maximum trim blade life, remove accumulated tape "trimmings" from front tape guide. If using other than Neutape, there may be an adhesive build up on front and back blades - this should be removed as well as any residue on front and back tape guides.

2. When replacing trim blades, <u>DO NOT</u> adjust blade holder. Trim blade must not touch lower matrix - there should be no metal to metal contact.

PLACE ORDER NOW for ADDITIONAL ROLLS of NEUTAPE CLEAR or YELLOW OPAQUE

16mm Neutape \$1.95/roll 12 rolls per Package

35/70 Neutape \$2.85/roll 8 rolls per Package

FOR BEST RESULTS and a PERFECT SPLICE EVERY TIME, USE NEUTAPE SPLICING TAPE

Neumade



PRODUCTS CORPORATION

BOX 568, 720 WHITE PLAINS RD., SCARSDALE, N.Y. 10583

Now!

Neulape FOR PHOTOGARD

For best Splicing results on film treated with 3M Photogard, be sure to use our specially developed splicing tape for Photogard (clear only).

<u>16MM</u>

<u>35MM</u>

,

PHG-16 NEUTAPE \$3.20/Roll (10 Pkg.) PHG-35 NEUTAPE \$4.40/Roll (8 Pkg.)



Noumade

PRODUCTS CORPORATION 200 Connecticut Ave: P.O. Box 5001 Norwalk, CT. 06856

Veumade SINCE 1916

APRIL 1, 1991 5 . 1. 14

W.

35MM PARTS LIST -- MODELS #35-SS....#35-DS....#35-SDS

FAX (203) 866-7522

NEUMADE PRODUCTS CORPORATION

. יג'

200 CONNECTICUT AVENUE/P.O. BOX 5001/NORWALK, CT 06856 (203) 866-7600 FAX (203) 866-7522

..

۰.

ŝ

; 1	REF.	NO.	PART NO.		CRIPTION	. * *		
				<u>, , , , , , , , , , , , , , , , , , , </u>	CRIFTION	2		PRICE
	1	3.44 1	NT-6B	TAPE CUTTER		stre		\$ 5.95
i .	· 2		NT-7B NT-8	BLADE PRESS	URE PLATE			3.90
	4		NT-1B	BLADE POSIT REAR BLADE	IONING SCR	KEM /	All Constants	5.20
٤.,	5		NT-2B	FRONT BLADE			· · · ·	24.50
	6	,	NT-2C	BLADE HOLDE	R SCREW &	WASHER 3	a an	24.50
1,	[~] 7	transi ta i		JOIM PERC P	UNCH,			.60
	8		NT-35DB	35MM PERF D	+ + + + + + + + + + + + + + + + + + +	OLD AS SET	r only)	212.00/set
:	10		NT-35PC NT-35DC	PUNCH MOUNT	ING SCREW			.70
	11		NT-9B	DIE MOUNTIN	G SCREW &	WASHER		.60
			NT-9BS	FILM CUTTER STRAIGHT FI	LM CHUMMER	(35-SS & 3	35-DS)	74.50
:			NT-9BD	DIAGONAL FI	LM CUTTER	FOR #35-5L	15	76.00 74.50
	12	¥.	NT-9C	FILM CUTTER	MOUNTING	SCREW & 2	SPACERS	.80
	13 14		NT-16B	- TAPE HOLDER	BRACKET	A Star		38.00
	15		NT-12B NT-12C	TAPE HOLDER	ROLLER		and a second	23.00
	16		NT-16C	TAPE ROLLER	RETAINER	ASSEMBLY	· · · ·	13.50
			NT-28B	TAPE HOLDER COMPLETE SE	COND WARE	SCREW	0)1 // 7 m	. 45
	17		NT-3B	PERFORATOR	PUNCH BASE	NOLDER ADL	O-ON KIT	59.00
	18	· • •	NT-38L~g~	(LH GUIDE PO	ST W/BOLT	& WASHER		84.00 22.00
	19		NT-38R	RH GUIDE PO	ST W/BOLT	& WASHER	a lain ant	22.00
•	20 21		NT-4	GUIDE POST	SPRING			7.90
	22		NT-22B NT-11C	UPPER JAW				110.00
	23		NT-21B	HANDLE STOP	SCREW & N	UT	1.1	.90
	24		NT-21C	STRIPPER PL		L SPACER		32.00
	25		NT-11	HANDLE		· · · · · · · · · · · · · · · · · · ·		68.00
	[#] 26 27	e tij o Ako A	NT-4H	"HANDLE PIVO	P PIN & SE	T SCREW	a this graphical	8.90
	28	ب	NT-22H NT-221	UPPER JAW P	VOT PIN &	SET SCREW		9.50
	29		NT-225	UPPER JAW P UPPER JAW SI	PRING	BOLT SPAC	ER"& NUT	
	30		NT-224	UPPER JAW SI	PACER	· · · · · · · · · · · · · · · · · · ·		5.40 12.00
1	31		NT-18B	BASE CLEAN-C	OUT PLATE			15.00
	32 .33		NT-18C	PLATE MOUNTI	NG SCREW	1. 1. 1.	i in the second	.45
	34		NT-13B NT-13C	REAR TAPE GU	JIDE ·		$(1,1) \in \{1,2,\dots,n\}$	9.50
	35		NT-15B	REAR TAPE GU	NIDE SCREW			.45
	36		NT-15C	FRONT TAPE (ў а		10.50
	37		NT-17B	RUBBER FEET	(SET OF 4)	Y , 2		.45 4.80
* <u>\$25.00</u> NET MINIMUM ORDER								
	463.	UU NET	MINIMUM OF	DER				
				•			 The state of the s	
·*#:*							And the second	10月1日 建
		MA						
й т	· .	t the second		JDIO-VISUAL, TELEVISION	PHOTOGRAPHIC A	ND MOTION PICTU	REEQUIPMENT	
5 1		1	•	1	िन (च			·····································
						a a constant a substant a	n orsennen setter bry	an a